

PortaCom



PortaCom is a flexible, high-performance wired intercom system. Built smart and simple, PortaCom gives you two channels without sacrificing power or quality. It is expandable, portable or rack mountable. It even has an optional battery supply module for remote locations.

Best of all PortaCom is priced to sell to the junior high school theater, the local cable studio or the high school football coach.



FOR MORE INFORMATION PLEASE CALL:

800.262-4671

www.anchoraudio.com

MADE IN THE USA!

2 Channel, Wired Full Duplex Systems

High Performance - Low Cost

AC/DC Operable

Portable or Rackmountable (1 U Rack Space)

Durable Lightweight Metal Packs

Up to 20 Headset Capacity

Standard Microphone Cable/3 Pin XLR Connectors

2-YEAR WARRANTY!

4 HEADSET PACKAGE (COM-40FC/C)

4 Headsets with Cables Package includes:

PC-100 power console, four dual earpiece H-200 headsets, four BP-200 belt packs, four EX-50M 50' cables, one CC-15F deluxe carrying case and one CC-PC cable bag.

6 HEADSET PACKAGE (COM-60FC/C)

6 Headsets with Cables Package includes:

PC-100 power console, six dual earpiece H-200 headsets, six BP-200 belt packs, one B3-100 branch box, seven EX-50M 50' cables, one CC-15F deluxe carrying case and one CC-PC cable bag.



PORTACOM

TWO-CHANNEL WIRED INTERCOM SYSTEM



H-200S

Single-earpiece headphones with Lo-Z, noise-canceling microphone.



H-200


Dual-earpiece headphones with Lo-Z, noise-canceling microphone.

SYSTEM SPECIFICATIONS


| | |
|-------------------------|--|
| Operating distance: | up to 2,500ft. or (765m) (combined cable length) |
| Normal line level: | -15dBV |
| Signal-to-noise ratio: | -65dB |
| Distortion: | < 0.5% |
| Interconnecting cables: | standard 1-pair shielded mic cable with 3-pin XLR connectors (heavy-duty cable recommended for cable runs greater than 250ft.) |
| Compatibility: | generally compatible with industry standard system (contact Anchor Audio for more information) |

| | |
|------------------|--|
| Connector (4): | 4-pin XLR, female |
| Microphone type: | dynamic, low impedance |
| Dimensions: | 3.5 x 7.4 x 7.9" (89 x 188 x 201mm) |
| Weight: | H-200: 16oz., H-200S: 13oz. |

BP-200 Belt Pack



FRONT



BACK

Lightweight aluminum belt pack with volume control, A/B channel switch and mic and call button with LED indicator.

| | |
|--------------------------|-----------------------------------|
| Input line connector: | 3-pin XLR, female |
| Headset connector: | 4-pin XLR, male |
| Bridging impedance: | 10kΩ minimum |
| DC current requirements: | 20mA maximum |
| Dimensions: | 3.6 x 2.6 x 2.1" (91 x 66 x 53mm) |
| Weight: | 0.46lbs. (0.2Kg.) |

PC-100 Two-Channel Power Console



FRONT

Power console with four outputs; rack-mountable. Includes wall-mount AC adapter.

| | |
|-------------------------------|---|
| Output connectors (4): | 3-pin XLR, male |
| Voltage output to belt packs: | 22 volts DC |
| Maximum current capacity: | 400mA |
| Maximum belt packs: | 20 BP-200 belt packs |
| Input power requirements: | 24VAC, 50/60Hz, 750mA; or 30-40VDC, 500mA |
| Dimensions: | 1.75 x 8.5 x 4.5" (45 x 216 x 114mm) |
| Weight: | 3.6lbs. (1.7Kg.) |
| AC power adapter: | Anchor model AC-20 |
| input voltage: | 120VAC, 60Hz |
| output voltage/current: | 24VAC @ 750mA |

B3-100 Branch Box



FRONT



BACK

3-Station branch box for expanding PortaCom systems.

| | |
|------------------------|---|
| Input connector (1): | 3-pin XLR, female |
| Output connectors (3): | 3-pin XLR, male |
| Dimensions: | 1.9 x 4.1 x 4.25" (48 x 105 x 108mm) |
| Weight: | 1.2lbs. (0.5Kg.) |



3415 Lomita Blvd. • Torrance, CA 90505 • 800.262.4671 • Fax: 310.784.0066